

## Coaxial Test Kit

### FEATURES:

- ❖ Coverage From DC-50GHz
- ❖ Low VSWR
- ❖ Low Insertion Loss
- ❖ Stainless Steel

### APPLICATIONS:

- ❖ Test Bench
- ❖ Test Lab
- ❖ Production Test



DC-26 GHz TEST KIT CKT26

### DESCRIPTION:

Cernexwave's **CKT Series Test Kits** consist of five (5) attenuators, three (3) adapters, and one (1) termination.

Model	Components	Frequency (GHz)	Description	Attenuation (dB)	Power (W)	Insertion Loss (dB)	VSWR
CKT6	CFADC060302	DC-6	Fixed Attenuator	3±0.30	2	-	1.15
	CFADC060602	DC-6	Fixed Attenuator	6±0.30	2	-	1.15
	CFADC061002	DC-6	Fixed Attenuator	10±0.50	2	-	1.15
	CFADC062002	DC-6	Fixed Attenuator	20±0.50	2	-	1.15
	CFADC063002	DC-6	Fixed Attenuator	30±0.75	2	-	1.15
	CSM-SM6	DC-6	SMA-M to SMA-M Adapter	-	-	0.1	1.15
	CSM-SF6	DC-6	SMA-M to SMA-F Adapter	-	-	0.1	1.15
	CSF-SF6	DC-6	SMA-F to SMA-F Adapter	-	-	0.1	1.15
	CCLDC0601	DC-6	Termination	-	1	-	1.2
	CSM-SMCFX2-20	DC-6	Conforming Cable Assembly				
CKT18	CFADC180302	DC-6	Fixed Attenuator	3±0.60	2	-	1.15
	CFADC180602	DC-6	Fixed Attenuator	6±0.750	2	-	1.15
	CFADC181002	DC-6	Fixed Attenuator	10±1.25	2	-	1.15
	CFADC182002	DC-18	Fixed Attenuator	20±1.50	2	-	1.25
	CFADC183002	DC-18	Fixed Attenuator	30±2.00	2	-	1.25
	CSM-SM18	DC-18	SMA-M to SMA-M Adapter	-	-	0.1	1.15
	CSM-SF18	DC-18	SMA-M to SMA-F Adapter	-	-	0.1	1.15
	CSF-SF18	DC-18	SMA-F to SMA-F Adapter	-	-	0.1	1.15
	CCLDC1801	DC-18	Terminations	-	1	-	1.3
	CSM-SMCFX2-20	DC-18	Conforming Cable Assembly				
CKT26	CFADC260301	DC-26	Fixed Attenuator	3±0.30	1	-	1.35
	CFADC260601	DC-26	Fixed Attenuator	6±0.30	1	-	1.35



## Coaxial Test Kit

	CFADC261001	DC-26	Fixed Attenuator	10±0.50	1	-	1.35
	CFADC262001	DC-26	Fixed Attenuator	20±0.75	1	-	1.35
	CFADC263001	DC-26	Fixed Attenuator	30±0.80	1	-	1.35
	CSM-SM26	DC-26	SMA-M to SMA-M Adapter	-	-	0.1	1.25
	CSM-SF26	DC-26	SMA-M to SMA-F Adapter	-	-	0.1	1.25
	CSF-SF26	DC-26	SMA-F to SMA-F Adapter	-	-	0.1	1.25
	CCLDC26U5	DC-26	Termination	-	0.5	-	1.3
	CSM-SMCFX2-20	DC-26	Conforming Cable Assembly				
CKT40	CFADC400301	DC-40	Fixed Attenuator	3±0.80	1	-	1.4
	CFADC400601		Fixed Attenuator	6±0.80	1	-	1.4
	CFADC401001		Fixed Attenuator	10±1.00	1	-	1.4
	CFADC402001		Fixed Attenuator	20±1.00	1	-	1.4
	CFADC403001		Fixed Attenuator	30±1.00	1	-	1.4
	C29M-29M		2.9mm-M to 2.9mm-M Adapter	-	-	0.15	1.6
	C29M-29F		2.9mm-M to 2.9mm-F Adapter	-	-	0.15	1.6
	C29F-29F		2.9mm-F to 2.9mm-F Adapter	-	-	0.15	1.6
	CCLDC4001		Termination	-	1	-	1.25
CKT50	CFADC5003U5	DC-50	Fixed Attenuator	3±1.50	0.5	-	1.75
	CFADC5006U5		Fixed Attenuator	6±1.50	0.5	-	1.75
	CFADC5010U5		Fixed Attenuator	10±1.50	0.5	-	1.75
	CFADC5020U5		Fixed Attenuator	20±2.00	0.5	-	1.75
	CFADC5030U5		Fixed Attenuator	30±2.00	0.5	-	1.75
	C24M-24M		2.4mm-M to 2.4mm-M Adapter	-	-	0.15	2
	C24M-24F		2.4mm-M to 2.4mm-F Adapter	-	-	0.15	2
	C24F-24F		2.4mm-F to 2.4mm-F Adapter	-	-	0.15	2
	CCLDC50U5		Termination	-	0.5	-	1.3
CKT65	CFADC6503U5	DC-65	Fixed Attenuator	3±1.50	0.5	-	1.75
	CFADC6506U5		Fixed Attenuator	6±1.50	0.5	-	1.75
	CFADC6510U5		Fixed Attenuator	10±1.50	0.5	-	1.75
	CFADC6520U5		Fixed Attenuator	20±2.00	0.5	-	1.75
	CFADC6530U5		Fixed Attenuator	30±2.00	0.5	-	1.75
	C18M-18M		1.85mm-M to 1.85mm-M Adapter	-	-	0.15	2
	C18M-18F		1.85mm-M to 1.85mm-F Adapter	-	-	0.15	2
	C18F-18F		1.85mm-F to 1.85mm-F Adapter	-	-	0.15	2
	CCLDC65U5		Termination	-	0.5	-	1.3

SPECIFICATIONS MAY CHANGE WITHOUT NOTICE